Product Line

WG-RACK

Type

RM-WG-T4

Supported Models WATCHGUARD FIREBOX T70

DIMENSIONS	1.3/2U
COLOR	WatchGuard Red
PRODUCT DIMENSIONS (height x width x depth)	57 x 482 x 217 mm 2.24 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

1. Place the power supply on the rack and tie it down with 2 zip ties.
2. Remove the screw from the side of your WatchGuard Firebox T70 with the Torx key.
3. Place your WatchGuard on the rack, fix the WatchGuard with the screw on the side of the appliance.
4. Tie the excess length of the power cable down with the 3rd zip tie.
5. Remove the label from its carrier and place it above the connectors on the front.
6. Connect the cables from your WatchGuard to the connectors.
7. Place your WG-Rack in your 19 inch rack.
8. Place the Rackmount.IT front plate BELOW the WG-Rack in your 19 inch rack. Together they are 2U high.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	WG-Rack + RJ45 couplers + front plate
3	Zip ties
1	Torx key
1	Adhesive label
9	Cables - 0.5 meter

Industrial version is supplied with shielded couplers and cables

Consider the environment, recycle where applicable.

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 6 - 26-10-2018

EMEA Office
Nonnenveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
559 S Interstate 35, Suite 350
Round Rock - TX 78664
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT